

# IBM TotalStorage® DS8700 Disk Storage 1

## Microcode Bundle 76.31.55.0 v1 Release Note Information

Release Date: July 2, 2013

### VRMF Level Data Results:

VRMF level From:	76.31.42.0
VRMF Level To:	76.31.55.0
Report for:	All DS8700

## Code Bundle Contents

DS8000 Code Bundle Level	SEA or LMC Version: Used with dscli <i>ver</i> command.	CLI Client Level	Storage Manager Code Level
76.31.55.0	6.6.31.390	6.6.31.390	5.6.31.1113

## Overview of new features and functions supported by Microcode Release 76.31.55.0 for DS8700, 242x model 941.

### Features at a glance:

- none

### General:

- Global Mirror improvements for low bandwidth connections
- DA and DDM error handling improvements
- Improved error handling for drives with slow response times

**This is a new microcode release only supports the DS8700.**

### Select Modifications Included in this Release Note:

This is a list of some modifications contained across one or more LIC (License Internal Code) or microcode release(s). The potential impact is variable. Specific environments may aggravate or degrade the potential impact. Problem(s) fixed and reported in this release note may not be in higher levels of code bundles.

### Definition of Problem Severity:

- 1 High Impact - Acute: An irrecoverable error with potential loss of data.  
- Serious: An irrecoverable error with potential loss of access to data.
- 2 Moderate - A function not operational and/or performance might be degraded.
- 3 Service - A recoverable error (no impact) and service improvements.
- 4 Improvements - Improvement changes for better Usability and Serviceability.

**HIPER: High Impact problem that is Pervasive: 3 or more occurrences**

# IBM TotalStorage® DS8700 Disk Storage

## Microcode Bundle 76.31.55.0 v1 Release Note Information

2

### **Acute: An irrecoverable error with potential loss of data.**

#### **Smart Rebuild scan changed to once an hour from once a day**

- 1. Problem Description:** The smart rebuild scan has been changed to run once an hour instead of once a day.
  - 2. Potential Impact of Problem:** loss of data
  - 3. Problem Severity:** HIPER
  - 4. Pervasive Problem:** Yes
- ID#: 284782

#### **FlashCopy target volumes have stale R0 data**

- 1. Problem Description:** In a CKD environment FlashCopy target volumes can have stale R0 data due to a microcode logic error.
  - 2. Potential Impact of Problem:** loss of data
  - 3. Problem Severity:** HIPER
  - 4. Pervasive Problem:** Yes
- ID#: 264749

#### **BE504940 multiple sector LRC is detected**

- 1. Problem Description:** Parity checking does not check the entire sector due to a microcode logic error. Parity should check the entire sector and correct any parity error.
  - 2. Potential Impact of Problem:** loss of data
  - 3. Problem Severity:** High Impact
  - 4. Pervasive Problem:** No
- ID#: 276086

#### **Background media scan causes incorrect LBA calculation**

- 1. Problem Description:** Background media scan will calculate incorrect Logical Base Address (LBA) when converting the component LBA to an array LBA if the address is greater than 32 bits on a RAID6 array. This affects LUNs that are greater than 2TB in size.
  - 2. Potential Impact of Problem:** loss of data
  - 3. Problem Severity:** High Impact
  - 4. Pervasive Problem:** No
- ID#: 283506

### **Serious: An irrecoverable error with potential loss of access to data.**

#### **Internal I/O fabric error leaves host adapter link light on**

- 1. Problem Description:** During a recursive fabric error recovery the host adapter link light is left on but the adapter will not respond to I/O requests.
  - 2. Potential Impact of Problem:** loss of access
  - 3. Problem Severity:** HIPER
  - 4. Pervasive Problem:** Yes
- ID#: 276605

# IBM TotalStorage® DS8700 Disk Storage

## Microcode Bundle 76.31.55.0 v1 Release Note Information

3

### **DA adapter fenced by repeated showstop errors**

- 1. Problem Description:** If BGMS attempts to repair an LBA that is beyond the useable area of the drive the DA adapter will have repeated showstop errors until the adapter is fenced, only RAID 6 arrays are exposed.
- 2. Potential Impact of Problem:** loss of access
- 3. Problem Severity:** HIPER
- 4. Pervasive Problem:** Yes

ID#: 275724

### **Direct attached iSeries host port login is not processed correctly**

- 1. Problem Description:** Direct attached iSeries host has successful fabric login but port login fails, preventing remote IPL of the new host.
- 2. Potential Impact of Problem:** loss of access
- 3. Problem Severity:** HIPER
- 4. Pervasive Problem:** Yes

ID#: 279507

### **PPRC resume can cause copy relationship ID to incorrect**

- 1. Problem Description:** After some PPRC suspends, loss of all paths for example, the PPRC resume can result in new copy relationship IDs. This could potentially prevent hyperswap.
- 2. Potential Impact of Problem:** loss of hyperswap capability
- 3. Problem Severity:** High Impact
- 4. Pervasive Problem:** No

ID#: 279746

### **Cache deadlock during destage cause host reboot**

- 1. Problem Description:** Cache destage selects strides with no busy tracks first. If the first track in a stride is busy the other tracks are ignored. This can lead to a deadlock condition and result in the host rebooting.
- 2. Potential Impact of Problem:** loss of access
- 3. Problem Severity:** High Impact
- 4. Pervasive Problem:** No

ID#: 275846

### **Fiber Channel Loop errors causes DAHP to reject DDMs**

- 1. Problem Description:** When DAHP is enabled some Fiber Channel loop error recovery scenarios will result is DDMs being slow to respond. This can result in DAHP rejecting DDMs for being slow, and can result in degraded ranks.
- 2. Potential Impact of Problem:** loss of access
- 3. Problem Severity:** High Impact
- 4. Pervasive Problem:** No

ID#: 279289

# IBM TotalStorage® DS8700 Disk Storage

## Microcode Bundle 76.31.55.0 v1 Release Note Information

4

### **Moderate: A system path is not operational and performance might be degraded.**

#### **Global Mirror fatal error due to stale commands due to network issues**

- 1. Problem Description:** Network issues lead to stale revertible commands being received at the GM secondary which leads to a GM fatal condition.
- 2. Potential Impact of Problem:** GM suspend
- 3. Problem Severity:** Moderate
- 4. Pervasive Problem:** Yes

ID#: 241033

#### **PPRC Path State Change messages not handled like multi-host SIM**

- 1. Problem Description:** PPRC Path State Change messages are not handled the same as multi-host SIM messages when multi-host SIM is enabled. This can cause problems with console messages.
- 2. Potential Impact of Problem:** job abends
- 3. Problem Severity:** Moderate
- 4. Pervasive Problem:** No

ID#: 275880

#### **Hyper PAV alias device goes long busy for 2 minutes**

- 1. Problem Description:** If midway through processing a command chain and a unit check is encountered we will return long busy to the host for 2 minutes due to a microcode logic error
- 2. Potential Impact of Problem:** 2 minute device long busy
- 3. Problem Severity:** Moderate
- 4. Pervasive Problem:** No

ID#: 282025

#### **Long I/O response time during RAID 6 DDM rejection**

- 1. Problem Description:** During array metadata update all alpha components in the array are updated. If one of the drives is slow to respond to the metadata update then I/O is held until the drive responds
- 2. Potential Impact of Problem:** degraded performance
- 3. Problem Severity:** Moderate
- 4. Pervasive Problem:** No

ID#: 276112

#### **Host adapter microcode logic error recovery takes longer than time-out**

- 1. Problem Description:** A host adapter error causes the adapter to request reset causing warmstart to extent to 7 seconds. If host has an I/O time-out of 5 seconds then an application error will occur.
- 2. Potential Impact of Problem:** loss of path(s)
- 3. Problem Severity:** Moderate
- 4. Pervasive Problem:** No

ID#: 283103

# IBM TotalStorage® DS8700 Disk Storage

## Microcode Bundle 76.31.55.0 v1 Release Note Information

5

### **Service: A recoverable error, Service improvements.**

#### **FlashCopy control block update conflict**

- 1. Problem Description:** During control block update the lock does not cover the status field. This microcode logic error causes a warmstart.
  - 2. Potential Impact of Problem:** warmstart
  - 3. Problem Severity:** Service
  - 4. Pervasive Problem:** Yes
- ID#: 271715

#### **PPRC command reject can result in a warmstart**

- 1. Problem Description:** On a highly utilized PPRC link a command reject result in a warmstart due to a microcode logic error
  - 2. Potential Impact of Problem:** warmstart
  - 3. Problem Severity:** Service
  - 4. Pervasive Problem:** No
- ID#: 275799

#### **Metro Mirror or Global Mirror control block conflict**

- 1. Problem Description:** Due to a microcode logic error a warmstart to resolve a control block conflict can occur
  - 2. Potential Impact of Problem:** warmstart
  - 3. Problem Severity:** Service
  - 4. Pervasive Problem:** Yes
- ID#: 248217

#### **zHigh Performance FICON microcode logic error causes warmstart**

- 1. Problem Description:** When running Global Mirror or Global Copy with zHPF it is possible for command processing to result in a microcode detected error and a warmstart.
  - 2. Potential Impact of Problem:** warmstart
  - 3. Problem Severity:** Service
  - 4. Pervasive Problem:** Yes
- ID#: 276801

#### **Destage of cache data can encounter a microcode logic error**

- 1. Problem Description:** Due to a microcode logic error a warmstart can occur during cache destage. This error will result in a warmstart
  - 2. Potential Impact of Problem:** warmstart
  - 3. Problem Severity:** Service
  - 4. Pervasive Problem:** Yes
- ID#: 273131

#### **Update the order of part replacement for SRC BED10861**

- 1. Problem Description:** The primary part is the I/O enclosure power supply. The second and third parts changed order to make the PCIe/SPCN card the secondary part and the mid-plane the last part to repair this failure.
  - 2. Potential Impact of Problem:** none
  - 3. Problem Severity:** Service
  - 4. Pervasive Problem:** No
- ID#: 270217

# IBM TotalStorage® DS8700 Disk Storage

## Microcode Bundle 76.31.55.0 v1 Release Note Information

6

### **CEC hard drive rebuild fails because no matching level found**

- 1. Problem Description:** CEC hard drive rebuild process checks the VRMF level, searching for a matching level. If an ICS disk was used to install an the fix level is updated and causes hard drive rebuild to fail.
  - 2. Potential Impact of Problem:** none
  - 3. Problem Severity:** Service
  - 4. Pervasive Problem:** Yes
- ID#: 264701

### **PE Package is missing LPAR data**

- 1. Problem Description:** Intermittently the PE Package is missing the LPAR files due to a microcode logic error on the HMC.
  - 2. Potential Impact of Problem:** delayed problem analysis
  - 3. Problem Severity:** Service
  - 4. Pervasive Problem:** No
- ID#: 277537

### **After microcode update a storage enclosure reports not in a good state**

- 1. Problem Description:** After microcode update a storage enclosure will report not in a good state. The enclosure is in a good state.
  - 2. Potential Impact of Problem:** False error reported
  - 3. Problem Severity:** Service
  - 4. Pervasive Problem:** Yes
- ID#: 255938

### **I/O Priority Manager monitor mode does not work without LIC key**

- 1. Problem Description:** Due to a microcode logic error DS GUI does not allow the user to access IO Priority Manager to enable monitor mode without the feature key being installed.
  - 2. Potential Impact of Problem:** DS GUI will not set IOPM monitor mode
  - 3. Problem Severity:** Service
  - 4. Pervasive Problem:** No
- ID#: 277415

## **Improvements: Improvement for better usability**

### **LSS and PPRC path information added to error logging**

- 1. Problem Description:** LSS and path information added to the error logs for PPRC path problems. Previously a statesave is required to get the LSS path information which is required for problem analysis.
  - 2. Potential Impact of Problem:** reduced problem analysis time
  - 3. Problem Severity:** Improvement
  - 4. Pervasive Problem:** N/A
- ID#: 283045

# **IBM TotalStorage® DS8700 Disk Storage**

## **Microcode Bundle 76.31.55.0 v1 Release Note Information**

7

### **Trademarks**

The following terms are trademarks of the International Business Machines Corporation in the United States, other countries, or both.

- > AIX
- > Enterprise Storage Server
- > ESCON
- > FICON
- > i5/OS
- > iSeries
- > IBM
- > pSeries
- > S/390
- > System Storage
- > TotalStorage
- > z/OS
- > zSeries

IBM, the IBM logo, and ibm.com are trademarks or registered trademarks of International Business Machines Corp., registered in many jurisdictions worldwide. Other product and service names might be trademarks of IBM or other companies.

A current list of IBM trademarks is available on the web at Copyright and trademark information at <http://www.ibm.com/legal/us/en/copytrade.shtml>.

Adobe, the Adobe logo, PostScript, and the PostScript logo are either registered trademarks or trademarks of Adobe Systems Incorporated in the United States, and/or other countries.

Java and all Java-based trademarks and logos are trademarks or registered trademarks of Oracle and/or its affiliates.

Linux is a trademark of Linus Torvalds in the United States, other countries, or both.

Microsoft, Windows, and Windows NT are trademarks of Microsoft Corporation in the United States, other countries, or both.

© Copyright IBM Corp. 2004, 2011

### **Notices**

This information was developed for products and services offered in the U.S.A. IBM may not offer the products, services, or features discussed in this document in other countries. Consult your local IBM representative for information on the products and services currently available in your area. Any reference to an IBM product, program, or service is not intended to state or imply that only that IBM product, program, or service may be used. Any functionally equivalent product, program, or service that does not infringe any IBM intellectual property right may be used instead. However, it is the user's responsibility to evaluate and verify the operation of any non-IBM product, program, or service. IBM may have patents or pending patent applications covering subject matter described in this document. The furnishing of this document does not give you any license to these patents. You can send license inquiries, in writing, to:  
IBM Director of Licensing  
IBM Corporation  
North Castle Drive  
Armonk, NY 10504-1785  
U.S.A.

# **IBM TotalStorage® DS8700 Disk Storage** 8

## **Microcode Bundle 76.31.55.0 v1 Release Note Information**

**The following paragraph does not apply to the United Kingdom or any other country where such provisions are inconsistent with local law:**

INTERNATIONAL BUSINESS MACHINES CORPORATION PROVIDES THIS PUBLICATIONS "AS IS" WITHOUT WARRANTY OF ANY KIND, EITHER EXPRESS OR IMPLIED, INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTIES OF NON-INFRINGEMENT, MERCHANTABILITY OR FITNESS FOR A PARTICULAR PURPOSE. Some states do not allow disclaimer of express or implied warranties in certain transactions, therefore, this statement may not apply to you.

This information could include technical inaccuracies or typographical errors. Changes are periodically made to the information herein; these changes will be incorporated in new editions of the publication. IBM may make improvements and/or changes in the product(s) and/or the program(s) described in this publication at any time without notice.